

Value+

Digital Multimeters

- With Inductive Charging Feature (MM66 series) which is Eco-friendly (no disposable batteries are needed) and convenience to use
- Input Jack Indicators which helps to remind users to plug-in the correct jacks
- Using Vertical Alignment Display (MM66 series) allows :
 - 1) Larger viewing angle;
 - 2) Faster response;
 - 3) Sharper Contrast;
 - 4) Easier read under strong light.



Digital Multimeters



MM66B



MM66C



MM66E



MM65B



MM65C



MM65E

Functions		MM65B	MM65C	MM65E	MM66B	MM66C	MM66E
DC Voltage	200mV/2V/20V/200V 600mV/6V/60V/600V	±(0.5%+3)	±(0.5%+3)	±(0.5%+3)	±(0.5%+3)	±(0.5%+3)	±(0.5%+3)
AC Voltage	2V/20V/200V 600mV/6V/60V/600V 750V	±(0.8%+10)	±(0.8%+10)	±(0.8%+5)	±(0.8%+10)	±(0.8%+10)	±(0.8%+5)
DC Current	200µA/2mA/20mA/200mA 60µA/600µA/6000µA/60mA/600mA	±(1.2%+10)	±(1.2%+10)	±(0.8%+3)	±(1.2%+10)	±(1.2%+10)	±(0.8%+3)
AC Current	10A 20mA/200mA 60µA/600µA/6000µA/60mA/600mA	±(2%+5)	±(2%+5)	±(2%+10)	±(2%+5)	±(2%+5)	±(2%+10)
Resistance	200Ω/2kΩ/20kΩ/200kΩ/2MΩ 600Ω/6kΩ/60kΩ/600kΩ/6MΩ/60MΩ 20MΩ	±(0.8%+3)	±(0.8%+3)	±(0.8%+3)	±(0.8%+3)	±(0.8%+3)	±(0.8%+3)
Temperature	-20~1000°C 0~1832°F	±(1%+25)	±(1%+25)	±(1%+4)	±(1%+25)	±(1%+5)	±(1%+4)
Frequency	10Hz/100Hz/1kHz/10kHz/100kHz/1MHz/10MHz	±(1.2%+6)	±(1.2%+6)	±(1.2%+6)	±(1.2%+6)	±(1.2%+6)	±(1.2%+6)
Capacitance	20mF 60mF	±(5%+10)	±(5%+10)	±(1%+3)	±(5%+10)	±(5%+10)	±(1%+3)
Line		✓	✓	±(4%+4)	✓	✓	±(4%+4)
NCV		✓	✓	✓	✓	✓	✓
Auto Ranging		✓	✓	✓	✓	✓	✓
Battery Test	1.5V/9V	✓	✓	✓	✓	✓	✓
Diode		✓	✓	✓	✓	✓	✓
Continuity Buzzer		✓	✓	✓	✓	✓	✓
True RMS		✓	✓	✓	✓	✓	✓
Data Hold		✓	✓	✓	✓	✓	✓
Auto Power Off		✓	✓	✓	✓	✓	✓
Display Mode		Twisted Nematic			Vertical Alignment		
Display Backlight		✓	✓	✓	✓	✓	✓
Max Display		1999	1999	5999	1999	1999	5999
Power By		1.5V (R6) x 2			3.7V (14500) x 1		
Inductive Charging		✓	✓	✓	✓	✓	✓

* All information provided are subject to change without prior notice.



Your Distributor :



Futronix Co.

HONG KONG

www.futronix-hk.com

info@futronix-hk.com