

Value+

Light Meters & Sound Level Meters

- Easy to use
- Good shape for easy holding

Light Meters

- Unit selectable (Lux and Fc selectable)

Sound Meters

- Checking the environmental noise
- Able to measure A, C Frequency-Weighting
- Able to measure Linearity range of sound pressure
- Time Weighting selectable (Fast and Slow selectable)



Light Meter & Sound Level Meter



Basic Functions	LM51C
Measurement Range	200/2000/20000/200000 Lux 200/2000/20000 Fc
Repeatability	±2.0%
Resolution	0.1/1/10/100 Lux 0.1/1/10 Fc
Accuracy	±(3.0%+15)
Special Features	
Max Display	1999
Measuring speed	3 times/sec
Data hold	✓
MAX mode	✓
Lux / Fc switchable	✓
Low power indication	✓
LCD Backlight	✓
Auto power off	✓
Powered By	9V (6F22) x 1

* All information provided are subject to change without prior notice.



Basic Functions	SL51A
Measurement Range	35dB~130dB
Frequency response to sound pressure measurement	31.5Hz~8.5kHz
Linearity range of sound pressure	50dB
Resolution	0.1dB
Accuracy	±1.5dB
Special Features	
Max Display	1999
Data hold	✓
MAX mode	✓
Frequency weighting characteristics	A,C
Time weighting	Fast / Slow
Over range indication	✓
Low power indication	✓
LCD Backlight	✓
Auto power off	✓
Powered By	9V (6F22) x 1

* All information provided are subject to change without prior notice.

Futronix Co.

Rm 609 Lee On Industrial Building,
70 Hung To Road, Kwun Tong, Kowloon,
HONG KONG

Tel : (852) 3580 7725

Fax : (852) 3753 4800

e-mail : info@futronix-hk.com



Your Distributor :